

Virtual Hardware	Compatible to	Hardware ID	Interface	Nominal speed	Driver	VMX entry (example)
VMCI Device		PCI\VEN_15AD&DEV_0740	PCI		VMware Tools	[none]
VMWare SVGA II		PCI\VEN_15AD&DEV_0405	PCI		VMware Tools	[none]
IDE-Controller	Intel 82371 AB/EB	PCI\VEN_8086&DEV_7111	PCI	66 MBit		[none]
SATA-AHCI-Controller (3.0)		PCI\VEN_15AD&DEV_07E0	PCI	6 Gbit		sataX.present="true" sataX.virtualDev="ahci"
NIC (flexible)	AMD PCNET Family Ethernet Adapter	PCI\VEN_1022&DEV_2000	PCI	10 MBit 1 GBit (accel.)	<a href="http://www.symantec.com/connect/sites/default/files/AMD_Inc.PCnet_4.51.0.0.zip">http://www.symantec.com/connect/sites/default/files/AMD_Inc.PCnet_4.51.0.0.zip</a> Accelerated: VMWare Tools	[none]
NIC (VMXNET 2)		PCI\VEN_15AD&DEV_0720	PCI	1 GBit	VMware Tools	ethernet0.virtualDev = "vmxnet"
NIC (VMXNET 3)		PCI\VEN_15AD&DEV_07B0	PCIe	10 GBit	VMware Tools	ethernet0.virtualDev = "vmxnet3"
NIC (E1000)	Intel PRO/1000 MT (82546)	PCI\VEN_8086&DEV_100F	PCI	1 GBit	<a href="http://downloadcenter.intel.com">http://downloadcenter.intel.com</a>	ethernet0.virtualDev = "e1000"
NIC (E1000E)	Intel 82574L Gigabit NC	PCI\VEN_8086&DEV_10D3	PCIe	1 GBit	<a href="http://downloadcenter.intel.com">http://downloadcenter.intel.com</a>	ethernet0.virtualDev = "e1000e"
SCSI (BusLogic Parallel)	BusLogic BT-946C (BA80C30)	PCI\VEN_104B&DEV_1040	PCI	10 MBit	<a href="http://www.vmware.com">http://www.vmware.com</a> (vm SCSI-1.2.0.4.flp)	[none]
SCSI (LSI Logic Parallel)	LSI Logic 1020/1030 Ultra320 SCSI	PCI\VEN_1000&DEV_0030	PCI	320 MBit	<a href="http://www.dell.com/support/drivers/us/en/19/DriverDetails?driverId=r67876">http://www.dell.com/support/drivers/us/en/19/DriverDetails?driverId=r67876</a> <a href="http://www.lsi.com/Search/Pages/downloads.aspx?k=LSIU320">http://www.lsi.com/Search/Pages/downloads.aspx?k=LSIU320</a>	scsi0.virtualDev = "lsilogic"
SCSI (LSI Logic SAS)	LSI SAS1068	PCI\VEN_1000&DEV_0054	PCIe	3 GBit	<a href="http://www.lsi.com/products/storagecomponents/Pages/LSISAS1068.aspx">http://www.lsi.com/products/storagecomponents/Pages/LSISAS1068.aspx</a>	scsi0.virtualDev = "lsisas1068"
SCSI (VMWare Paravirtual)		PCI\VEN_15AD&DEV_07C0	PCIe		VMware Tools	scsi0.virtualDev = "pvscsi"
NVMe		PCI\VEN_15AD&DEV_07F0	PCIe			nvme0.present = "true"
USB 1.1 Controller		PCI\VEN_15AD&DEV_0774	PCI	12 MBit		
USB 2.0 Controller		PCI\VEN_15AD&DEV_0770	PCI	480 MBit		
USB 3.0 Controller		PCI\VEN_15AD&DEV_0779	PCIe	5 GBit		usb_xhci.present = "true"
Sound (SB16)	Sound Blaster 16		ISA			sound.virtualDev = "sb16"
Sound (Ensoniq)	Creative AudioPCI ES1371	PCI\VEN_1274&DEV_1371	PCI			[none]
Sound (HD Audio)		HDAUDIO\FUNC_01&VEN_15AD&DEV_1975	PCI			sound.virtualDev = "hdaudio"